

ECOGEN SERIES

BACK UP POWER FOR OFF-GRID APPLICATIONS

15 kW



ECOGEN

Backup Power for Alternative Energy Systems

Whether the off-grid lifestyle is a choice or a necessity, you are responsible for producing the energy you consume—even when there's no sun or wind. Ensure you never have dead batteries with the Generac EcoGen—the only automatic standby generator designed and warranted specifically for off-grid use with an alternative energy system.

How Does the Generac EcoGen Work?

In an alternative energy system, the generator is an important source of backup power when other resources are insufficient for the demand.

- ① Solar cells and/or wind turbines generate DC electric current.
- ② The DC current enters the inverter charger, and then the battery bank.
- ③ The inverter takes DC power from the battery bank, converts it to AC electricity, and sends the AC power to your home's electrical panel.
- ④ If the battery level drops to a preset point, perhaps because there is no solar or wind power available, the inverter automatically signals the EcoGen generator to start up.
- ⑤ The EcoGen delivers AC power to the inverter, which simultaneously sends AC power to your home's electric panel and sends DC power to the battery bank until it is charged to an acceptable level.



Patented G-Flex™ Technology

Exceptional Fuel Efficiency. Best in Class Quiet Operation.

Traditional home standby generators have to run at a constant speed—traditionally 3600 RPMs—to produce usable electricity. Patented G-Flex™ technology from Generac changes all of that. It allows the Generac EcoGen home standby generator to vary its speed based upon electrical demand. The EcoGen will run more slowly—and quietly—than when the family is up and using many appliances. The EcoGen will consume less fuel when demand is light, saving you money. Lower speeds mean quieter operation, so your peace and quiet will go on undisturbed. Even better, G-Flex™ technology delivers electricity with less than 2.0% total harmonic distortion (THD)—lower even than the IEEE standards for utility power—to properly power today's sophisticated alternative energy systems. The EcoGen delivers best in class fuel efficiency, sound, output and power quality, making it an easy choice when it comes to off-grid solutions.

Designed Specifically for Off-Grid Use

Unprecedented Service Intervals

The EcoGen's exclusive premium oil recovery and circulation system virtually halts oil degradation, and allows for 500 hours between oil changes—five times the industry standard.

Two-Wire Start

Factory-equipped to easily connect to the inverter control wires so that the inverter to automatically start and stop the generator in order to charge the system batteries as necessary.

Limited Warranty

Unlike conventional home standby generators used in an alternative energy system, the EcoGen is backed by a 3-year/2000 hour limited warranty.



15 KILOWATTS



FEATURES



OHVI® ENGINE

The Generac OHVI® engine, specifically designed for generator use, provides the reliability to power through the most severe outages. Engineered and built in the USA.



EVOLUTION™ CONTROLLER

The next generation of intuitive controllers, the Evolution controller features a multilingual, two-line LCD text display with color-coded backlit buttons.



CONVENIENT INSTALLATION

Can be installed only 18" from the home, if located away from doors, windows, and fresh air intakes, unless otherwise directed by local codes.

* Total harmonic distortion (THD) less than 2.0%—lower than both IEEE standards for utility power and published numbers for competitive air-cooled home standby generators.

† Built in the USA using domestic and foreign parts.



RHINOCOAT

Our durable RhinoCoat powder-coat finish helps make sturdy aluminum enclosures perfect for all weather conditions. Enclosure is able to withstand 150 mph winds.



FUEL OPTIONS WITH TOOL-LESS CONVERSION

The Generac EcoGen runs on LP fuel or natural gas, and easily converts during installation without the need for tools.

GENERATOR

Model 6103 (15 kW)

Rated Maximum Continuous Power Capacity (NG/LP)	15,000 W / 15,000 W
Rated Voltage	240 V
Rated Maximum Continuous Load Current – 240 Volts	62.5 / 62.5
Main Line Circuit Breaker	65 Amps
Phase	1
Number of Sliprings	3
Rated AC Frequency	60Hz
Power Factor	1
Battery Requirement (not included)	Group 26R 12 Volts and 525 Cold-cranking Amperes Minimum
Unit Weight (Pounds / Kilos)	536 / 243.1
Dimensions (L x W x H) Inches [mm]	48 x 25 x 29 [1218 x 638 x 732]
Sound output in dB(A) at 23 ft. with generator operating at normal load	63

ENGINE

Type of Engine	Generac OHVI V-twin	
Number of Cylinders	2	
Displacement	999cc	
Cylinder Block	Aluminum w/Cast Iron Sleeves	
Valve Arrangement	Overhead Valve	
Ignition System	Solid-state with Magneto	
Governor System	Electronic	
Compression Ratio	9.5:1	
Starter	12 Vdc	
Engine Oil Capacity Including Filter (quarts / liters)	1.9 Qt / 1.8 L	
Oil Reservoir Capacity (quarts / liters)	3.75 Qt / 3.55 L	
Engine Operating RPM	2700-3600	
Fuel Consumption	Natural Gas - ft ³ /hr (m ³ /hr)	Liquid Propane - ft ³ /hr
1/2 load	134 (3.79)	47.6 (1.32) [4.99] (gal/hr)
Full Load	281 (7.96)	103.6 (2.87) [10.86] (E1/hr)

Required fuel pressure to generator fuel inlet at all load ranges - 10 to 12 inches of water column for liquid propane gas, 5-7 inches water column for natural gas.

CONTROLS

2-Line Plain Text LCD Display	Simple user interface for ease of operation
2-Wire start	Allows for easy inverter control correction
Mode Switch - Auto	Puts unit in standby mode, waiting for inverter start call.
- Off	Stops unit. Power is removed. Control and charger still operate.
- Manual/Test (start)	Start with starter control, unit stays on.
Starter Lock-out	Starter cannot re-engage until 5 sec. after engine has stopped.
2.5 Amp Smart Battery Charger	Standard
Automatic Voltage Regulator with Overvoltage Protection	Standard
Automatic Low Oil Pressure Shutdown	Standard
Overspeed Shutdown	Standard, 72Hz
High Temperature Shutdown	Standard
Overcrank Protection	Standard
Safety Fused	Standard

* Rating definitions - Standby: Applicable for supplying emergency power for the duration of the charging period. No overload capability is available for this rating. (All ratings in accordance with BSS514, ISO3046 and DIN6271). * Maximum wattage and current are subject to and limited by such factors as fuel Btu content, ambient temperature, altitude, engine power and condition, etc. Maximum power decreases about 3.5 percent for each 1,000 feet above sea level; and also will decrease about 1 percent for each 12° C (10° F) above 15.5° C (60° F). Not for sale in California.

Global Dealer Service Network

Generac's commitment to service includes scheduled maintenance programs, warranty assistance and emergency service to ensure that Generac customers are never left powerless. The largest global dealer network has factory-trained technicians on staff and maintains large inventories of Generac parts, components and accessories. Find a dealer near you at generac.com.

